#### TECHNICAL INFORMATION



#### SUBMINIATURE PENTODE

# **TYPE**

# CK5672

The CK5672 is a filament type pentode of subminiature construction designed for use as a power

amplifier in wearable and portable equipment. The flexible terminal leads may be soldered or welded directly to the terminals of circuit components without the use of sockets. Standard inline subminiature sockets may be used by cutting the leads to a suitable length.

#### MECHANICAL DATA

ENVELOPE: T-2X3 Glass

BASE: None (0.016" tinned flexible leads. Length: 1.5" min. Spacing: 0.048" center-to-center)

TERMINAL CONNECTIONS:

Lead 1 Plate Lead 2 Grid #2 Lead 3 Filament, positive Lead 4 Grid #1

Lead 5 Filament, negative:

Grid #3

MOUNTING POSITION: Any

#### ELECTRICAL DATA


DIRECT INTERELECTRODE CAPACITANCES: (μμfds) Δ		
Grid #1 to Plate Input Output	0.14 2.8 3.5	
RATINGS - ABSOLUTE MAXIMUM VALUES:		
Filament Voltage (dc) Plate Voltage Grid #2 Voltage Total Cathode Current	100	volts volts volts ma.
CHARACTERISTICS AND TYPICAL OPERATION:		
Filament Voltage (dc) Filament Current Plate Voltage Grid #2 Voltage Grid #1 Voltage Plate Current Grid #2 Current Transconductance Plate Resistance Load Resistance Distortion (approx.) Power Output Peak AF Signal Voltage	50 67.5 67.5 - 6.5 3.25 0.95 650 125 20 10 65	

▲ Without shield.


.285<sup>7</sup>' max. 385' max. Red Dot

Tentative Data











Printed in U.S.A.



# AVERAGE PLATE CHARACTERISTICS (Triode Connected)







Printed in U.S.A.

....



